



# Sales, Service, Calibration, and Training

YCG, Inc.

2603 Reach Rd, Rear Bldg, Williamsport, PA 17701

Phone: 570-494-1150 ext 0 | Fax: 570-494-1021



## Chrono-USB v2 Quick Fact Sheet

Accuracy ..... 0.05% rdg + 3  $\mu$ sec

Range ..... 200 – 30,000  $\mu$ sec

Resolution ..... 0.1  $\mu$ sec

Power ..... USB 5V DC

LCD Display ..... 8 digits

Over Range Error ... Indicates Start, but no Stop pulse

### Serial Output

Transmit Format      B#####E      B..Begin, #..Data, E..End

Example: B0005012E = 501.2  $\mu$ sec

Error Code            B error E      (start pulse is received but no stop pulse is received)

### Serial Input

Reset Code            Send ASCII "R" or Decimal 82

Trigger Inputs ..... +12V rising edge

Front Panel Reset .... Clears LCD and sends B000000E Serial output